

MOON PENDANT

















Variants		Item No.	Colour Temp
Blk	Wht		
22772	22773	MOON-PDT	TRIO
22774	22775		
22776	22777		
22778	22779		

Thank you for purchasing your new MOON-PDT Light, Please take the time to read and understand the instruction sheet below. Failure to do so may void warranty.

Specifications

Voltage:	240V	CCT:	3000K - 4000K - 5700K (Switchable)	Dimmable:	Yes	Lifespan:	50,000hrs
Power:	6/9W	IP Rating:	20	CRI:	>90		

Please refer to the data sheet for lumen output.

Optional Optics:			
01 Flood	02 Spot	03 Opal	04 Tube
<p>1 Select suitable CCT / Power you need.</p> 	<p>2 Select the optics, then lock the safety wire.</p> 	<p>3 Rotate the optics on the LED engine in clockwise direction, make sure it was locked until you hear "click".</p> 	<p>4 Turn off the power.</p> 
<p>5 Open 3 hole on the ceiling.</p> 	<p>6 Mounted Plastic expansion screws with plastic hammer.</p> 	<p>7 Drill the screw into the ceiling and leave 5mm in the outside.</p> 	<p>8 Loosen the pendant box.</p> 
<p>9 Open the pendant box and take out the terminal bracket.</p> 	<p>10 Insert the terminal bracket and rotate it until it fixed.</p> 	<p>11 Tighten the bracket screw.</p> 	<p>12 Connecting the wiring accordingly.</p> 
<p>13 Close the terminal box and fix.</p> 	<p>14 Tighten the screw of pendant box and fix.</p> 	<p>15 Installation finishes.</p> 	<p>16 Turn on the power.</p> 

Note: -The lamp must be installed by professional electrician
-Ensure the power supply is switched off before fitting this product

-Do not touch the lamp when in use
-Keep away from hot steam and corrosive gas